

STEP

1


Choose Installation Location



Water Heater
Basements
Laundry rooms
Sump Pumps



Bathrooms



Kitchens

SPECIFICATIONS

- Transmitter: 2.71" L x .95" W x .56" D
- Tamper Switch: Included inside transmitter
- Probe Dimensions: .7" W x 1.77" L x .38" D
- Cord length 6'
- Wireless signal range: 600ft (200M), open air
- Transmitter frequency: 345 MHz
- Unique code ID:
- RF Peak field strength: typical 36000 uV/m at 3m
- Operating Temperature: 32° to 122°F (0° to 50°C)
- Relative Humidity: 5 - 95% Non-Condensing
- Storage Temperature: -40° to 140°F (-40° to 60°C)
- Supervisory keep-alive interval: 70 minutes
- Code outputs: tamper, tamper restore, alarm, alarm restore, low battery
- Batteries: 2 – CR2032. Approximate Battery Life: 5 years
Replace Batteries: (2) Panasonic CRT2032, Energizer CR2032, or Duracell DL2032

THIS IS A QUICK GUIDE FOR EXPERIENCED INSTALLERS ONLY. FOR DETAILED INSTALLATION INSTRUCTION REFER TO DOCUMENTATION FOUND AT WWW.WINLAND.COM

STEP
2



Remove protective battery tab-pull

STEP
3




Attach transmitting unit to wall with adhesive strips (included)

STEP
4



Mount the Transmitter above the floor level (as high as reasonably possible) to prevent water damage.



Attach probe to floor or floor baseboard with adhesive strips (included). Tie off extra cord as needed or desired.

STEP
5

“Learn” WaterBug transmitter into the control panel



Enable “Programming Mode”



Open and close the case to “tamper” the device

ADD

Customize name and settings as desired and touch “ADD”

NEED HELP?

800-635-4269 Ext 1

techsupport@winland.com

D-011-0175
Rev. A

FCC / IC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
 - Increase the separation between the equipment and receiver.
 - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
 - Consult the dealer or an experienced radio/TV technician for help.
- This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.
- Cet appareil est conforme avec Industrie Canada exempts de licence standard RSS (s). Son fonctionnement est soumis aux deux conditions suivantes: (1) cet appareil ne doit pas provoquer d'interférences et (2) cet appareil doit accepter toute interférence, y compris celles pouvant causer un mauvais fonctionnement de l'appareil.

In accordance with FCC requirements of human exposure to radio frequency fields, the radiating element shall be installed such that a minimum separation distance of 20 cm is maintained from the general population.

FCC: 2ABBZ-WIN-WATER-345
IC: 11817A-WINWATER345

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This Class B digital apparatus complies with Canadian ICES-3B. Cet appareil numérique de la classe B est conforme à la norme NMB-003 du Canada.

MANUFACTURER HEREBY DISCLAIMS ALL WARRANTIES AND REPRESENTATIONS, WHETHER EXPRESS, IMPLIED, STATUTORY OR OTHERWISE INCLUDING (BUT NOT LIMITED TO) ANY WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE WITH RESPECT TO THESE PRODUCTS AND ANY RELATED SOFTWARE. MANUFACTURER FURTHER DISCLAIMS ANY OTHER IMPLIED WARRANTY UNDER THE UNIFORM COMPUTER INFORMATION TRANSACTIONS ACT OR SIMILAR LAW AS ENACTED BY ANY STATE. (USA only) SOME STATES DO NOT ALLOW THE EXCLUSION OF IMPLIED WARRANTIES, SO THE ABOVE EXCLUSION MAY NOT APPLY TO YOU. THIS WARRANTY GIVES YOU SPECIFIC LEGAL RIGHTS AND YOU MAY ALSO HAVE OTHER LEGAL RIGHTS THAT VARY FROM STATE TO STATE. MANUFACTURER MAKES NO REPRESENTATION, WARRANTY, COVENANT OR PROMISE THAT ITS ALARM PRODUCTS AND/OR RELATED SOFTWARE (S) WILL NOT BE HACKED, COMPROMISED AND/OR CIRCUMVENTED; (S) WILL PREVENT, OR PROVIDE ADEQUATE WARNING OR PROTECTION FROM, BREAK-INS, BURGLARY, ROBBERY, FIRE, OR (S) WILL WORK PROPERLY IN ALL ENVIRONMENTS AND APPLICATIONS.